



# ScanSnap iX500



*Digitalize y guarde en Mac o PC y ahora Android o iOS. "Vamos sin PC!"*



iOS



ScanSnap

# ¡Sencillo, Rápido y Poderoso!

## Accelerate yourself with ScanSnap iX500!

**Corre en computadoras Windows & Mac OS X**

Y ahora con dispositivos móviles y tablets con iOS y android

**Creación de PDF's con un botón**

Solo apila documentos en el alimentador y presiona el botón de escaneo.

**Maneja una pila de documentos.**

Carga hasta 50 páginas en el alimentador automático de documentos

**Escanea ambos lados de cada página al mismo tiempo**

Las imágenes son automáticamente enderezadas y cortadas con los lados blancos removidos.

**Escaneo de documentos rápido y confiable**

Escanea hasta 25 páginas por minuto con el avanzado manejo del papel.

**Escanea tarjetas de negocios a documentos de gran tamaño**

Escanea documentos A3, fotos y mucho mas



iOS



### Escanea directamente a dispositivos móviles

Rápidamente direcciona a la computadora para escanear un archivo PDF o JPEG a un dispositivo móvil o Tablet con iOS y android.

### Microprocesador GI incorporado

El procesador GI desempeña el mejoramiento de imagen inteligente responsable de imágenes visualmente increíbles con resultados más rápidos y conectividad más sofisticada.



\*procesamiento de imagen: correcciones de imagen y salidas de imagen.

\*soporta wi-fi WPS y wireless LAN

\*soporta USB 3.0



### Sistema avanzado de alimentación de papel

Heredando la tecnología superior en alimentación de papel de nuestros escaners de nivel profesional, El IX500 logra una confiabilidad excepcional en alimentación usando "separating roller" tecnología que reduce atascos y multi alimentación.



### Detección de alimentación ultrasónica

Para seguridad adicional, el IX500 usa ondas sónicas para ayudar a asegurar cada página escaneada.



# ScanSnap iX500

## Ahorre tiempo con su Rapido Menú!



Quick Menu for Windows® shown

El menú rápido del scansnap para pc y mac automáticamente sale después del escaneo para proporcionarte una gran variedad de formas para ser inmediatamente productivo con tus escaneos. Este puede ser personalizable para mostrar solo tus favoritos, recomendaciones e incluso mostrar perfiles personalizables.

## Acelera la creación de PDF de búsqueda

Hacer archivos PDF de búsqueda en el punto de escaneo es una gran manera de mantener a estos instantáneamente accesibles, y ahora tu puedes crear un PDF de búsqueda a una velocidad cercana a la de un PDF estándar.



## Scan there! ScanSnap Folder

Scan to virtually any application or web service that can open, insert or attach a PDF or JPEG file from your Windows® computer.



## Organiza tarjetas de negocios



CardMinder for Windows® shown

Escanea, almacena y edita información de tarjetas de negocios con el software CardMinder incluido para MAC y PC e incluso exporta información de otras aplicaciones como son directorios, Excel y Salesforce.

## Scan to Cloud

For the ultimate in accessibility to your scans across multiple platforms, computers and devices, iX500 provides operators a convenient way to scan directly to your existing Evernote, Dropbox, Google Docs, SugarSync and Salesforce accounts.



## Modelo de lujo del Scansnap ix500



Para usuarios de Windows®, Rack 2 filer Smart es una aplicación de escaneo y de visualización de contenido que incorpora un intuitiva biblioteca y una interfaz de carpeta que da a los usuarios una interacción disfrutable así como familiar con su papeleo escaneado. "Magic Desktop" está diseñado para organizar escaneos de scansnap como también memos e imágenes de dispositivos móviles y cargar tu información a Facebook.



# ScanSnap iX500

Especificaciones		
Nombre del Productor	ScanSnap iX500	
Tipo de escaner	Alimentador automatico de documentos (ADF) Escaneo Duplex	
Modos de Escaneo	Color, escala de grises, monocromatico, detección automatica (color/escala de grises/monocromatico)	
Sensor de Imágenes	Color CIS (Contact Image Sensor) x 2 (delante/atrás)	
Fuente de luz	Led 3 colores (Rojo / verde / azul)	
Velocidad de escaneo (A4 Retrato)	Automodo	Simplex y duplex, 25 páginas por minuto (ppm)
	Modo normal	Color y escala de grises 150 dpi, monocromatico 300 dpi, Simplex / duplex
	Modo mejorado	Color y escala de grises 200 dpi, monocromatico 400 dpi, simplex / duplex
	Modo superior	Color & Grayscale 300 dpi, Monochrome 600 dpi, Simplex/Duplex, 25 ppm
Document size	Normal Mode without Carrier Sheet	A4, A5, A6, B5, B6, Business Card, Post Card, Letter, Legal and Custom Size. Max: 8.5 X 14.17 in. (216 X 360 mm), Min: 2 X 2 in. (50.8 X 50.8 mm) Automatically recognizes document size.
	Normal Mode with Carrier Sheet	Use of a Carrier Sheet permits the scanning of A3, B4, 11 x 17 in. and photographs as well as the document sizes listed above
Multi-feed detection	Supported (Standard)	ultrasonic multi-feed detection sensor
	Paper Weight (Thickness)	• 11 to 56 lb (40 to 209 g/m) • A8 Size: 34 to 56 lb (127 to 209 g/m) • Cards: (ISO7810 ID-1 type conforming) can be used. (thickness 0.76 mm or less) • Embossed card : useable (Landscape only)
Paper Chute Capacity	Maximum 50 sheets (A4 (letter size) at 21 lb or 80 g/m	
Interface	USB 3.0 (USB 2.0 / USB 1.1 Compatible)	
Wi-Fi Interfacé	Observed standard	IEEE802.11b / IEEE802.11g / IEEE802.11n
	Communication mode	Infrastructure mode
	Frequency	2.412 GHz to 2.462 GHz / 2.412 GHz to 2.472 GHz
	Indoors, 50 m (Recommended: indoors, within 25 m) *May vary depending on the surrounding environment and the access point to be connected	
Power Requirement	AC 100 to 240 V, 50 / 60 Hz	
	Power Consumption	USB connected
Wi-Fi connected		Operating Mode: 20 W or less Standby Mode: 2.5 W or less
Operation Environment	Temperature	41 to 95 °F (5 to 35 °C)
	Relative humidity	20 to 80 % (No Condensation)
Dimensions (W x D x H)	11.5(W) x 6.2(D) x 6.6(H) in. (292 x 159 x 168 mm)	
Device Weight	6.62 lb (3.0 kg)	
Environmental Compliance	ENERGY STAR compliant / RoHS	
Driver	Specific driver Windows: Does not support Twain/ISIS • Mac OS: Does not support Twain	
Limited Warranty	1 Year Limited Warranty. For full details, visit <a href="http://www.fcpa.fujitsu.com/warranty">www.fcpa.fujitsu.com/warranty</a> or call (800) 626-4686	
Service Options	In-warranty Upgrade: Advance Exchange. Post-Warranty: Advance Exchange Plus, Depot Plus, ScanAid Kit, Cleaning and Consumable Kit. For full details all service programs, visit <a href="http://www.ImagingService.com">www.ImagingService.com</a>	

1: Scanning speeds may vary due to the system environment. Documents measuring 5.8 inches (148 mm) in length or less are scanned in "Best Mode", while other documents are scanned in "Better Mode". Only Computer connected ScanSnap iX500 is capable of scanning documents that exceed A4 size in length. ScanSnap iX500 supports the scanning of longer documents in all modes except in "Excellent Mode". Capacity varies depending upon paper weight. Some computers do not recognize the ScanSnap when it is connected to a USB 3.0 port. In this case, please use a USB 2.0 port. Only Android™ / iOS in case of Wi-Fi connection. Scanning speed depends on Country. EEE802.1X Authentication is not supported. Excluding the stacker and other external attachments. © FUJITSU LIMITED, a Fujitsu company, has determined that this product meets RoHS requirements (2002/95/EC).

Software	Windows	Mac OS
Driver <sup>2,13</sup>	ScanSnap Manager V6.0 ScanSnap Organizer V5.0	ScanSnap Manager V6.0 —
Applications	CardMinder™ V5.0	CardMinder™ V5.0
	ABBY FineReader for ScanSnap™ 5.0	ABBY FineReader for ScanSnap™ 5.0
	—	ABBY FineReader Express Edition for Mac 8.3
	Scan to Microsoft® SharePoint3.4	—
	Adobe Acrobat X Standard	—
Evernote for Win 4.5	—	Evernote for Mac 3.3

12: Twain or ISIS applications cannot be used directly. One button™ image file JPEG, PDF and searchable PDF) generation. These functions are not available when used with ScanSnap Manager (ScanSnap driver).

Included items		
• 1 ScanSnap	• 1 Safety Precautions	• 1 Rack2-Filer Smart with Magic Desktop (Bundled)
• 1 AC Cable	• 1 Setup DVD-ROM	
• 1 AC Adapter	• 1 Adobe Acrobat DVD-ROM (PC Only)	with ScanSnap iX500
• 1 USB cable (USB 3.0 Supported)	• 1 ScanSnap Carrier Sheet	Deluxe Only)

Consumables		
Description	Model Number	Remarks
Roller Set	PA03656-0001	Lifetime: Every 200,000 sheets or one year. (For ScanSnap iX500 only)
Cleaner F1	PA03950-0352	100 ml bottle For use on the Brake roller and Pick roller
Cleaning wipe	PA03950-0419	1 pack (24 sheets) For use on the Brake roller and Pick roller

\* These recommended lifetimes are for 21 lb (80 g/m) sized documents. Therefore, appropriate replacement lifetimes may vary from other document types.

©2012 Fujitsu Computer Products of America, Inc. All rights reserved. Fujitsu and the Fujitsu logo are registered trademarks of FUJITSU LIMITED. CardMinder™ Engine ©2011 ABBYY. OCR by ABBYY. Adobe and FineReader are trademarks of ABBYY. Adobe, Acrobat are either registered trademarks or tradenames of Adobe Systems Incorporated in the United States and/or other countries. Evernote is a registered trademark or trademark of Evernote Corporation. Google, Google Docs, Android and Google Play are registered trademarks of Google Inc. Intel, Pentium, and Intel Core are registered trademarks or trademarks of Intel Corporation in the United States and other countries. Microsoft, Windows, Windows Vista, Excel, PowerPoint, SharePoint and Internet Explorer are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries. Word is the product of Microsoft Corporation in the United States, Palestine and elsewhere. CRM are registered trademarks or trademarks of salesforce.com, inc. in the United States and other countries. ScanSnap, ScanSnap logo, ScanSnap Manager, ScanSnap Organizer, CardMinder and Rack2-Filer are registered trademarks or trademarks of FUJITSU LIMITED in Japan. Wi-Fi and Wi-Fi Protected Setup are trademarks of Wi-Fi Alliance. Other company names and product names are the registered trademarks or trademarks of the respective companies. Specifications are subject to change without notice. All statements herein are valid in the US for US residents only, are based on normal operating conditions, are for informational purposes only, and are not intended to create any implied warranty of merchantability or fitness for a particular purpose. DS397001130

Windows				
Compatible operating systems	Windows 8 (32-bit / 64-bit)	Windows 7 (32-bit / 64-bit)	Windows Vista (32-bit / 64-bit)	Windows XP (32-bit)
Driver/ Application <sup>14,15</sup>	ScanSnap Manager V6.0	Supported	Supported	Supported
	ScanSnap Organizer V5.0	Supported	Supported	Supported
	CardMinder™ V5.0	Supported	Supported	Supported
	ABBY FineReader for ScanSnap™ 5.0	Supported	Supported	Supported
	Scan to Microsoft® SharePoint3.4	Supported	Supported	Supported
	Adobe Acrobat X Standard <sup>16</sup>	Supported	Supported	Supported
Evernote for Win 4.5	Supported	Supported	Supported	Supported
Hardware Requirements	CPU <sup>20</sup>	Intel® Core™ 2 Duo 2.2 GHz or higher (Recommended: Intel® Core™ i5 2.5 GHz or higher)		
	Memory Capacity	64-bit: 2 GB or more (Recommended: 4 GB or more) 32-bit: 1 GB or more (Recommended: 4 GB or more)		
	Display	1,024 x 768 pixels or higher / 800 x 600 pixels or more		
	Disk Capacity	4,010 MB free hard disc space for installation		
	DVD-ROM Drive	Required for installation		
USB Port <sup>20,22</sup>	USB3.0 <sup>23</sup> / USB2.0 / USB1.1			

14: This product supports Microsoft Windows 15: Please refer to the ScanSnap Website for latest support information. For use with Service Pack 2 or higher: For use with Service pack 3 or higher: Requires Internet Explorer 7.0 or later, or Firefox 3.5 or later. Please refer to Adobe Systems Incorporated website for latest support information. Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. .NET Framework 3.5 SP1 will be installed (requires 500 MB of disk space) together with either ScanSnap Manager, ScanSnap Organizer or CardMinder™ for systems that do not have .NET Framework 3.5 SP1 installed. ScanSnap operates on both USB 2.0 and USB 3.0 without any difference in performance. Some computers do not recognize the ScanSnap when it is connected to a USB 3.0 port. In this case, please use a USB 2.0 port. \* System requirements may change depending on the duration of support and the support policy of the country that make the software listed in the table above.

Mac OS			
Compatible operating systems	Mac OS X v10.8	Mac OS X v10.7	Mac OS X v10.6
Driver/ Application <sup>24,25</sup>	ScanSnap Manager V6.0	Supported	Supported
	CardMinder™ V5.0	Supported	Supported
	ABBY FineReader for ScanSnap™ 5.0	Supported	Supported
	ABBY FineReader Express Edition for Mac 8.3	Supported	Supported
Evernote for Mac 3.3	Supported	Supported	Supported
Hardware Requirements	CPU <sup>28</sup>	Intel Core™ 2 Duo 2.2 GHz or higher (Recommended: Intel® Core™ i5 2.5 GHz or higher)	
	Memory Capacity	2 GB or more (Recommended: 4 GB or more)	
	Display	1,024 x 768 pixels or more	
	Disk Capacity	2,090 MB free hard disc space for installation	
	DVD-ROM Drive	Required for installation	
USB Port <sup>28,29</sup>	USB3.0 <sup>29</sup> / USB2.0 / USB1.1		

24: This product supports Mac operating systems. Please refer to the ScanSnap Website for latest support information. Recommended: 10.7.4 or later. Recommended: 10.6.8 or later. Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. ScanSnap operates on both USB 2.0 and USB 3.0 without any difference in performance. Some computers do not recognize the ScanSnap when it is connected to a USB 3.0 port. In this case, please use a USB 2.0 port. \* System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

### Rack2-Filer Smart V1.0 / Magic Desktop V1.0<sup>32,33</sup> System Requirements (Bundled with ScanSnap iX500 Deluxe only)

Compatible operating systems		Windows 8 (32-bit / 64-bit) <sup>34</sup>	Windows 7 (32-bit / 64-bit) <sup>35</sup>	Windows Vista (32-bit / 64-bit) <sup>36</sup>	Windows XP (32-bit) <sup>37</sup>
Hardware Requirements	CPU	Intel Pentium 4 1.8 GHz or higher (Recommended: Intel® Core™ 2 Duo 2.2 GHz or higher)			
	Memory capacity	2 GB or more (Recommended: 4 GB or more)			
	Display	1,024 x 768 pixels or higher			
	Disk Capacity	System drive <sup>38</sup>	—	64-bit: 2 GB or more	—
Supported scanners	Installation drive	1GB or more disc space* for each software			
	—	*Additional space is required for the data created by Rack2-Filer Smart and Magic Desktop			
Supported mobile devices		ScanSnap iX500, S1500, S1500M, S1300i, S1300, S1100			
Supported mobile devices	Model	iPad series, iPhone series (4 or later), iPod touch series (4th generation or later)			
	OS	iOS 4.3 or later			
	Application	Rack2-Filer Smart for iOS1.1.0 or later			

31: This product only supports Microsoft Windows 32: Please refer to the Rack2-Filer Smart Website and the Magic Desktop Website. For use with Service pack 1 or higher: For use with Service pack 2 or higher: For use with Service pack 3 or higher: This is the free capacity required when .NET Framework 4 is not installed.

Options		
Description	Model Number	Remarks
ScanSnap Carrier Sheet <sup>39</sup>	PA03360-0013	5 Carrier Sheets Intended for ScanSnap iX500, S1500, S1500M, S510, S510M, S500 and S500M
ScanSnap Bag	PA03951-0651	Intended for ScanSnap iX500, S1500M, S510, S510M, S500 and S500M

39: Although ScanSnap Carrier Sheets have a listed lifespan of 500 scans, the lifespan may vary with usage. ScanSnap Carrier sheets are intended to scan paper documents with weights of 120 g/m<sup>2</sup>. They also support the scanning of folded documents that are as large as 216 x 297 mm.

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local laws and laws, including, without limitation, copyright laws when using this scanner.

Fujitsu Computer Products of America, Inc.  
1250 East Arques Avenue Sunnyvale, CA 94085-4701 (800) 626-4686 (408) 746-6000  
• [info@fcpa.fujitsu.com](http://info.fcpa.fujitsu.com) <http://us.fujitsu.com/fcpa>

